



PRS-NSP Network Splitter



- ▶ **Two current-limited network tap-offs**
- ▶ **Supports redundant network connection on main loop**
- ▶ **Can feed power from an external supply to the network**
- ▶ **Indicators for power and fault status**

The network splitter is used in a network to provide two branches from the main cable run. It can use an external DC power supply, or it can use the power supply from the network controller. The unit automatically switches to the local power supply unit when it is connected to it, reducing the power drain on the main network. The network splitter can also function as a repeater, effectively extending the length of the main network another 50 meters.

Functions

The splitter inserts Praesideo units connected to a tap-off into the main network, however without the redundancy of the main loop. The maximum current supplied for each of the two tap-offs is separately selectable. External power from the local supply is used only for the tap-offs, and is not fed into the main system cable. The network splitter has two LEDs for diagnostic purposes.

Controls and indicators

- Power status LED
- Fault status LED
- Jumpers to configure tap-offs power behavior

Interconnections

- Two system network connections for main network
- Two system network connection for network tap-offs
- External power supply input

Certifications and Approvals

Region	Certification	
Europe	CE	
	TUEV-SUED	TUV Certificate IEC60849
	GL	GL-SOLAS
Safety	acc. to IEC 60065 / EN 60065	
Immunity	acc. to EN 55103-2 / EN 50130-4 / EN 50121-4	
Emissions	acc. to EN 55103-1 / FCC-47 part 15B	
Emergency	acc. to EN 60849 / EN 54-16 / ISO 7240-16	
Maritime	acc. to IEC 60945	

Parts Included

Quantity	Component
1	PRS-NSP Network Splitter
1	Mounting bracket
1	Power supply connector

Technical Specifications

Electrical

Power consumption	3.9 W (network)
-------------------	-----------------

External power supply

Voltage	24 to 56 VDC, 48 VDC nominal
---------	------------------------------

Current	2.5 A maximum (5 A peak <2 s)
---------	-------------------------------

Mechanical

Dimensions (H x W x D)	
------------------------	--

Without bracket	27 x 243 x 80 mm (1.1 x 9.6 x 3.1 in)
-----------------	---------------------------------------

With bracket	34 x 243 x 84 mm (1.3 x 9.6 x 3.3 in)
--------------	---------------------------------------

Weight	0.7 kg (1.5 lb)
--------	-----------------

Mounting	Bracket (two screws)
----------	----------------------

Color	Charcoal
-------	----------

Environmental

Operating temperature	-5 °C to +55 °C (+23 °F to +131 °F)
-----------------------	-------------------------------------

Storage temperature	-20 °C to +70 °C (-4 °F to +158 °F)
---------------------	-------------------------------------

Relative humidity	15% to 90%
-------------------	------------

Air pressure	600 to 1100 hPa
--------------	-----------------

Ordering Information

PRS-NSP Network Splitter

used in a network to provide two branches from the main cable run

PRS-NSP

Americas:
Bosch Communications Systems
12000 Portland Avenue South
Burnsville, Minnesota 55337, USA
Phone: +1-800-392-3497
Fax: +1-800-955-6831
audiosupport@us.bosch.com
www.boschsecurity.com

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: +31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2600
Fax: +65 6571 2698
apr.securitysystems@bosch.com
www.boschsecurity.com

Represented by